## Extension Module for V13 print board

Extension board

(only compatible with V13 print boards)

Connect to POWER-OUT on main V13 print

L (BROWN WIRE) Connect to L (66) on main V13 print

• N (BLUE WIRE) Connect to N (67) on main V13 print

PE (YELLOW/GREEN WIRE) Connect to PE (68) on main V13 print

PEN L17 PEN L18 OUTPUT OUTPUT GND (BLACK WIRE) Connect to GND (63) on main V13 print
RX (BLUE WIRE) Connect to TX (65) on main V13 print
TX (BROWN WIRE) Connect to RX (64) on main V13 print

## Installation Instructions:

1. Disconnect Power

2. Mount the extension module along side the main V13 print board.

3. Connect power supply from main print board to 100V-240V connection found at 1,2, & 3 on the extension module.

- 4. Connect TX (on main V13 print BUS 1) to RX (on Ext mod. BUS 1)
- 5. Connect RX (on main V13 print BUS 1) to TX (on Ext mod. BUS 1)
- 6. Connect GND (on main V13 print BUS) to GND (on Ext mod. BUS 1)

7. On the tablet go to setup and set the "extention module connected" setting to "on"